

<b>AMP</b>	<b>Bias</b>	<b>Thermal Circuit Breaker Value</b>	<b>Fuse Value</b>	<b>Fuse Value 240V (Export)</b>	<b>Carvin Replacement Part Number</b>	<b>Details</b>
VL100 Legacy	100mA	6 Amp	-		70-28106	THERMAL CIRCUIT BREAKER 6AMP
VL212 Legacy	100mA	6 Amp	-		70-28106	THERMAL CIRCUIT BREAKER 6AMP
MTS3200	100mA	6 Amp	-		70-28106	THERMAL CIRCUIT BREAKER 6AMP
MTS3212	100mA	6 Amp	-		70-28106	THERMAL CIRCUIT BREAKER 6AMP
X100B	100mA	-	6.3 Amp		70-12063	FUSE 320 6.30A SLOW BLOW 5X 20MM
X212B	100mA	-	6.3 Amp		70-12063	FUSE 320 6.30A SLOW BLOW 5X 20MM
V3	100mA	6 Amp	-		70-28106	THERMAL CIRCUIT BREAKER 6AMP
V3212	100mA	6 Amp	-		70-28106	THERMAL CIRCUIT BREAKER 6AMP
Nomad	75mA	-	3.0 Amp		70-12030	FUSE 320 3.00A SLOW BLOW 5X 20MM
Belair	75mA	-	3.0 Amp		70-12030	FUSE 320 3.00A SLOW BLOW 5X 20MM
Vintage 16	40mA	-	1 Amp		70-12010	FUSE 320 1.00A SLOW BLOW 5X 20MM
DCM600	3-5mV	-	15 Amp		70-22115	FUSE MDQ 15.00A SLOW BLOW 6.35X32MM
DCM1000	3-5mV	-	25 Amp		70-22125	FUSE MDA 25.00A SLOW BLOW 6.35X32MM
DCM1500	3-5mV	-	25 Amp		70-22125	FUSE MDA 25.00A SLOW BLOW 6.35X32MM
DCM2000	3-5mV	-	25 Amp		70-22125	FUSE MDA 25.00A SLOW BLOW 6.35X32MM
DCM2500	3-5mV	-	25 Amp		70-22125	FUSE MDA 25.00A SLOW BLOW 6.35X32MM
DCM2570	3-5mV	-	25 Amp		70-22125	FUSE MDA 25.00A SLOW BLOW 6.35X32MM
DCM1204	3-5mV	-	25 Amp		70-22125	FUSE MDA 25.00A SLOW BLOW 6.35X32MM
KB1000	3-5mV	-	25 Amp		70-22125	FUSE MDA 25.00A SLOW BLOW 6.35X32MM
RX800	3-5mV	-	25 Amp		70-22125	FUSE MDA 25.00A SLOW BLOW 6.35X32MM
RX1200	3-5mV	-	25 Amp		70-22125	FUSE MDA 25.00A SLOW BLOW 6.35X32MM
LS1523	3-5mV	-	15 Amp		70-22115	FUSE MDQ 15.00A SLOW BLOW 6.35X32MM
B1500	3-5mV	-	25 Amp		70-22125	FUSE MDA 25.00A SLOW BLOW 6.35X32MM
BX600/1200	3-5mV	-	15 Amp		70-22115	FUSE MDQ 15.00A SLOW BLOW 6.35X32MM
B1500	3-5mV	-	25 Amp		70-22125	FUSE MDA 25.00A SLOW BLOW 6.35X32MM
C1644P	3-5mV	-	25 Amp		70-22125	FUSE MDA 25.00A SLOW BLOW 6.35X32MM
RX800/1200	3-5mV	-	25 Amp		70-22125	FUSE MDA 25.00A SLOW BLOW 6.35X32MM
XP650	3-5mV	-	15 Amp		70-22115	FUSE MDQ 15.00A SLOW BLOW 6.35X32MM
XP880	3-5mV	-	15 Amp		70-22115	FUSE MDQ 15.00A SLOW BLOW 6.35X32MM
S400/S400D	-	-	3.0 Amp		70-12030	FUSE 320 3.00A SLOW BLOW 5X 20MM
AG100D	-	-	5 Amp		70-21050	FUSE ABC 5.00A FAST BLOW 6.35X32MM
PB200	-	-	5 Amp		70-21050	FUSE ABC 5.00A FAST 6.35X32MM
C844U	-	-	2 Amp		70-12020	FUSE 320 2.00A SLOW BLOW 5X 20MM
C1644U	-	-	2 Amp		70-12020	FUSE 320 2.00A SLOW BLOW 5X 20MM

C2444U	-	-	2 Amp		70-12020	FUSE 320 2.00A SLOW BLOW 5X 20MM
C3244U	-	-	2 Amp		70-12020	FUSE 320 2.00A SLOW BLOW 5X 20MM
SLP5600	-	-	10 Amp		70-22101	FUSE MDQ 10.00A SLOW BLOW 6.35X32MM
CG200	-	-	1.5 Amp		70-12015	FUSE 320 1.50A SLOW BLOW 5X 20MM
EQ2030	-	-	3 Amp		70-21030	FUSE ABC 3.00A FAST BLOW 6.35X32MM
EQ2015	-	-	3 Amp		70-21030	FUSE ABC 3.00A FAST BLOW 6.35X32MM
FX2	-	-	3 Amp		70-12030	FUSE 320 3.00A SLOW BLOW 5X 20MM
H400	-	-	3 Amp		70-12030	FUSE 320 3.00A SLOW BLOW 5X 20MM
LM12A	-	-	10 Amp		70-22101	FUSE MDQ 10.00A SLOW BLOW 6.35X32MM
LM15A	-	-	10 Amp		70-22101	FUSE MDQ 10.00A SLOW BLOW 6.35X32MM
PA620	-	-	5 Amp		70-21050	FUSE ABC 5.00A FAST BLOW 6.35X32MM
S16	-	-	1.5 Amp		70-12015	FUSE 320 1.50A SLOW BLOW 5X 20MM
SX100	-	-	5 Amp		70-21050	FUSE ABC 5.00A FAST BLOW 6.35X32MM
SX200	-	-	5 Amp		70-21050	FUSE ABC 5.00A FAST BLOW 6.35X32MM
SX300	-	-	5 Amp		70-21050	FUSE ABC 5.00A FAST BLOW 6.35X32MM
BR15	-	-	5 Amp		70-21050	FUSE ABC 5.00A FAST BLOW 6.35X32MM
FET900	100mA	-	10 Amp		-	-
PB900	100mA	-	-		-	-
MX1222S	100mA	-	-		-	-
MX822S	100mA	-	-		-	-
FET400	75mA	-	10 Amp		-	-
MX842	75mA	-	-		-	-
PB400	75mA	-	10 Amp		-	-
SX400	100mA	-	10 Amp		-	-
TS100	100mA	-	5 Amp	3 Amp	70-21050	FUSE ABC 5.00A FAST 6.35X32MM

\* For detailed instructions on how to bias your amp click on "how to bias", under the "Troubleshooting" tab.

\* For a replacement Fuse click on "Replacement Parts".

\* For an export models the fuse value is different.

\* (-) to specify not available, values subject to change.